



## Wired volumetric 30 m detector CH10063001



### DETECTION

|                                                   |                        |
|---------------------------------------------------|------------------------|
| Detector type                                     | <b>Wired</b>           |
| Detection distance                                | <b>30 m</b>            |
| Angle detection                                   | <b>50°</b>             |
| Installation height                               | <b>2.5 m ~ 4 m</b>     |
| Coverage                                          | <b>30 m x 20 m</b>     |
| Detection speed                                   | <b>0,2 m/s ~ 5 m/s</b> |
| Antimasking                                       | <b>Sí</b>              |
| PIR detection advance at ground level (PIR Creep) | <b>Sí</b>              |
| Detection technology                              | <b>Volumetric</b>      |
| 360PROtect™                                       | <b>Yes</b>             |

### POWER CONSUMPTION

|            |                           |
|------------|---------------------------|
| Power mode | <b>DC / AC</b>            |
| Voltage    | <b>10.5V ~ 30V / 24V</b>  |
| Amperage   | <b>18mA / 12mA ~ 30mA</b> |

### ESPECIFICACIONES TÉCNICAS

|                |           |
|----------------|-----------|
| LED indicators | <b>Sí</b> |
| Tamper         | <b>Sí</b> |

### GENERAL INFORMATION

|       |                     |
|-------|---------------------|
| Serie | <b>ADPRO® PRO E</b> |
|-------|---------------------|

### MATERIAL AND DIMENSIONS

|              |                           |
|--------------|---------------------------|
| Installation | <b>Wall / Post</b>        |
| Dimensions   | <b>358 x 188 x 290 mm</b> |
| Material     | <b>Asa</b>                |
| Net weight   | <b>1500 g</b>             |

### AMBIENT

|                       |                       |
|-----------------------|-----------------------|
| Operating temperature | <b>-20 °C ~ 60 °C</b> |
| Degree of protection  | <b>IP66</b>           |
| Use                   | <b>Indoor-outdoor</b> |

### SENSOR

|                        |            |
|------------------------|------------|
| Type of sensor         | <b>PIR</b> |
| Sensitivity adjustment | <b>Sí</b>  |

### INPUTS/OUTPUTS

|              |          |
|--------------|----------|
| Alarm output | <b>3</b> |
|--------------|----------|