



## AJAX

### Heat fire detector

### FIREPROTECT2-H-SB-W

#### TECHNICAL SPECIFICATIONS

Compatibility	<b>Hub Plus/Hub 2/Hub 2 Plus/Hub Hybrid</b>
LED indicators	<b>Yes</b>
LED colors	<b>Verde / Rojo / Amarillo</b>
Tamper	<b>Yes</b>
Tipo de notificación	<b>Acoustics</b>
Siren Volume	<b>85dB to 3 meter</b>
Temperature activation	<b>64°C</b>

#### AMBIENT

Operating temperature	<b>0 °C ~ 50 °C</b>
Degree of protection	<b>IP20</b>
Use	<b>Indoor</b>
Maximum humidity	<b>80%</b>

#### VIA RADIO

Frequency	<b>868.0 MHz ~ 868.6 MHz</b>
Transmission distance	<b>Up to 1700 m (without obstacles)</b>
Maximum power RF	<b>Hasta 20 mW</b>
Protocol	<b>Jeweller</b>

#### SENSOR

Type of sensor	<b>Temperature detection: thermistor</b>
----------------	--

#### DETECTION

Detector type	<b>Heat</b>
---------------	-------------

#### MATERIAL AND DIMENSIONS

Dimensions	<b>86 x 86 x 43.5 mm</b>
Net weight	<b>150 g</b>
Weight with packaging	<b>200 g</b>
Color	<b>White</b>

#### GENERAL INFORMATION

Technology	<b>Wireless</b>
Type	<b>Fire detector</b>

#### POWER CONSUMPTION

Battery model	<b>2 baterías de litio irremplazables</b>
Battery duration	<b>Up to 10 years</b>

#### DETECCIÓN (INCENDIO)

Termovelocimétrico	<b>10°C / min</b>
--------------------	-------------------

