



AJAX

40-zone wireless fire control panel

EN54-FIREHUB-W

ZONES

Maximum number of zones	40
Maximum number of rooms	80
Maximum number of devices	200
Keyboards	10
Sirens	10
Automated scenarios	64

POWER CONSUMPTION

Power mode	AC
Voltage	110V ~ 240V
Consumption (w)	60W
Battery support	Entry available
Battery model	7.4V 5 / 10 Ah

AMBIENT

Operating temperature	-10 °C ~ 40 °C
Degree of protection	IP20
Use	Indoor
Maximum humidity	75%

VIA RADIO

Frequency	868.0 MHz ~ 868.6 MHz
Transmission distance	Up to 1800 m (without obstacles)
Maximum power RF	Up to 25 mW
Protocol	Jeweller / Wings / TurboWings

CERTIFICATION

Grade	2
Normative	EN54-2 / EN54-4 / EN54-13 / EN54-21 / EN54-25

FEATURES

Number of users	200
Screen	Yes
Type of screen	IPS touchscreen
LED indicator	Yes
Screen resolution	1024 x 600

MATERIAL AND DIMENSIONS

Dimensions	263 x 223 x 54 mm
Net weight	1550 g
Weight with packaging	1900 g
Color	White

COMMUNICATION

Wi-Fi	Yes
Ethernet	Yes, 8P8C up to 100 Mbps
2G	Yes
4G	Yes

EXITS (FIRE)

Fault relay	1
Alarm relay	1

